











Product Name

UT-S1101

5KA Control Signal Surge Protector RS232

Key Feature







INTRODUCED

I. Summary

The UT-S1101 has to be installed by authorized professional person, to avoid incorrect installation or application to influence the normal working and lightning protection of devices, used in over-voltage protection from lightning and EMP of network equipments, like SWITCH, HUB, ROUTER, etc

II. Specification:

UT-S1101	UT-S2201
15 V	15 V
16.5 V	16.5 V
11 V	11 V
0.12 A	0.12 A
3 KA	5 KA
5 KA	10 KA
≤30 V	≤30 V
10 Ohm	10 Ohm
≤80 pF	≤80 pF
≤140 pF	≤140 pF
<1 ns	<1 ns
-40°C ~ 85°C	-40°C ~ 85°C
IEC61000-4-5	IEC61000-4-5
X	X
>1 MΩ	>1 MΩ
≤0.5 dB	≤0.5 dB
IP30	IP30
25 x 25 x 82	25 x 25 x 82
Shielded metallic aluminum	Shielded metallic aluminum
Connection terminal (RS-232)	Connection terminal (RS-232)
Class 4	Class 4
10 M	10 M
	15 V 16.5 V 11 V 0.12 A 3 KA 5 KA ≤30 V 10 Ohm ≤80 pF ≤140 pF <1 ns -40°C ~ 85°C IEC61000-4-5 X >1 MΩ ≤0.5 dB IP30 25 x 25 x 82 Shielded metallic aluminum Connection terminal (RS-232) Class 4

Operating Environment

Temperature: -40°C ~ 85°C; Relative humidity: 5% ~ 95%;

Barometric pressure: 70 kPa ~ 106 kPa

INFORMATION ORDER

MODEL: UT-S1101 5KA Control Signal Surge Protector RS232









